

PA-2100



Seven-Channel Power Amplifier

INTRODUCTION

An outstanding speaker requires an equally outstanding amplifier. This is the reason why we made the PA-2100. Combining with the optimized function and huge output capacity of the Procella Audio speaker, the PA-2100 has outstanding performance without compromise. It is an ideal match for Procella Audio passive speaker system. The high-efficiency seven-channel Class H circuit amplifier combined with excellent sound quality and huge power reserve can produce a completely transparent sound, effortlessly reproduce the complete dynamic range and strong substitution effect. PA-2100 is a 2100 watt seven-channel power amplifier, which can provide 8 ohm 300W x7. The amplifier adopts Hi-End grade design and structural technology, and completely adopts independent 7- channel separation and separation power amplifier circuit, which has more abundant power reserves.



TECHNICAL SPECIFICATIONS

7 channels rated output power 7*300W (8 ohms, mono, 1KHz, THD=1%)

Frequency response 20Hz-50kHz(±1/-3dB)

Distortion ≤0.09% (1KHz)

Not bridgeable

Support TRIGGER control

Comprehensive protection to prevent DC, thermal overload and short circuit

Overall gain 29.5dB

Two-year warranty

Neutrik® XLR balanced and RCA inputs

Front panel controls and LED indicators

High efficiency Green Audio Power™ design

Internally switchable power supply for either 115V or 230V operation

Dimensions (WxHxD) 450x440x195mm

Shipping Carton (WxHxD) 575x583x335mm

Net Weight 23 Kg

Shipping Weight 27 Kg

Certification CCC and CE

Assembly Designed by Procella Audio
Manufactured in China

